



产 品 手 册

仪器型号: BLMA 6080-100

西安安泰测试科技有限公司

仪器维修|租赁|销售|测试

地址:西安市高新区纬二十六路 369 号

网址: www.agitekservice.com

电话: 400-876-5512

座机: 029-88827159

STANDARD MODELS

Model	Frequency Range	Output Power P_N min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
BLMA 6080-100	6 ... 8 GHz	100 / 110	50 / 53 ±3	20 / 20	1200	4 HU, 630 mm	40

1 HU = 44.45 mm

STANDARD SPECIFICATIONS

Input Power:	0 dBm (1 mW) max.
Overdrive Protection:	up to +10 dBm for no damage
Input Impedance:	50 Ohm nominal
Output Impedance:	50 Ohm nominal
Input VSWR:	<2:1 typ.
Load VSWR:	infinite for no damage (100% mismatch tolerant)
	P_N -0.5 dB min. at VSWR 2:1
Spurious (at P_N):	-60 dBc min. (excluding harmonics)
Class of Operation:	A-linear or AB-linear

GENERAL

RF Input:	N-f, standard on rear panel
RF Output:	N-f, standard on rear panel
Mains Supply:	200 ... 240 V AC ±10%, 47 ... 63 Hz
Elapsed Time Meter:	via status display
Ambient Temperature:	0 ... +45 °C
Storage Temperature:	-25 ... 85 °C
Relative Humidity:	up to 95% (non-condensing)
Operating Altitude:	up to 2000 m above sea level
Vibration and Shock:	MIL-STD-810 G
Cooling:	forced air with integral blower air intake from front, air exhaust at rear

OPTIONS

A) RF-Sample Ports *)	L) LAN Remote Control
B) External Dual Directional Coupler	N) Harmonics Filtering *)
C) IEEE-488.2 GPIB Remote Control	R) RS-232C/RS-485 Remote Control
D) Front Panel RF Connectors	S) Internal RF Switching Unit *)
E) RF Power Indication (digital) *)	U) USB Remote Control
F) Gain Adjustment *)	W) Liquid Cooling
G) Output Isolator *)	X) External Control of other Amplifiers
H) DC Supply	

BLMA 6 ... 8 GHz Solid State Amplifiers

I) 3x 208 V AC / 60 Hz

*) These options may reduce output power and/or gain